# Terra<sup>™</sup> PIV

### Diode pumped Nd:YLF laser

Terra PIV is a dual oscillator/single head, high repetition rate, diode-pumped Nd:YLF laser. The Terra PIV offers the ultimate in flexibility for PIV and other dual output applications.

The combination of two independent oscillators allows complete control of pulse separation and pulse energy. Both oscillators in the Terra PIV system are identical in optical design giving temporally and spatially matched pulses for the highest degree of cross-correlation. Each oscillator can be independently triggered via TTL inputs. As an option, a compact, external combination box can be directly attached to the laser to provide for an easy and safe access to the beam combination optics.

The Terra PIV uses our proprietary intracavity frequency doubling to achieve high energy 527 nm outputs without resorting to the tight focusing (which can result in optical damage) necessary for extra-cavity doubling. Our proprietary pump chamber design increases the overall efficiency allowing for high pulse energy, excellent beam quality and long component lifetimes from a compact and robust diode-pumped package.



# Applications

#### Industry:

> Stent/Glass/PCB/Fine Metal Cutting

- > LCD/Solar Edge Deletion
- > Marking
- > Wafer Trimming
- > Micro-hole Drilling
- > Ceramics Scribing
- > Fine Wire Stripping
- > Diamond/Gemstone Processing

## Key Features

Velocimetry (PIV)

> Particle Image

> Ti:Sapphire pumping

- > Combustion Analysis
- > Laser Induced Fluorescence
- > LIDAR

Science:

- > Resonance Raman Spectroscopy
- > Chemical Analysis of Macromolecules

### > Laser Microprobe Analysis


> >60 mJ total energy at 1 kHz

- > Average power >100 W @ 3 kHz
- > Ideal for Particle Image Velocimetry
- > Independent external trigger for each oscillator
- > External and internal triggering
- > Built-in optics for beam combination
- > Record 3 min. diode module replacement
- > Proprietary optical cavity design for optimal laser performance
- > Flexible time delay and energy adjustment



Specifications <sup>1</sup>	527- 100-M	527- 80-M	527- 60-M	527- 40-M
Wavelength (nm)	527			
Energy per Oscillator at 0.1-1 kHz (mJ)	30	25	20	15
Total Pulse Energy at 0.1-1 kHz (mJ)	60	50	40	30
Pulse Repetition Rate (kHz) <sup>2</sup>	0.1-10			
Average Power @ 3 kHz (W)	100	80	60	40
Pulsewidth (ns)	< 210	< 230	< 250	< 270
Pulse-to-Pulse Stability (% RMS)	< 0.5			
Beam Pointing Stability (µrad)	< 25			
Beam Diameter at Output (mm) <sup>3</sup> , <sup>4</sup>	3.0			
Beam Quality (M²)	< 25			
Beam Divergence (mrad) <sup>4</sup>	8			
Time Jitter (ns RMS)	< 3			
Polarization <sup>5</sup>	Circular			

 $^1$  All specifications at 1kHz unless otherwise noted.  $^2$  Single shot to 0.1 kHz available with external trigger  $^3$  Typical measurement (±10%)  $^4$  Measured at 13.5% level at output window  $^5$  Cross-polarization available as option



Terra PIV Output Profile Smooth beam profile, ideal for PIV applications.

Dimensions			
Optical Head (LxWxH)	812 x 254 x 145 mm (31.9 x 10.0 x 5.6 in)		
Power Supply (LxWxH)	509 x 483 x 221 mm (20.0 x 19.0 x 8.7 in)		
Chiller (LxWxH)	699 x 483 x 492 mm (27.5 x 19.0 x 19.4 in)		
Weight			
Optical Head	31.5 kg (70 lbs)		
Power Supply	27 kg (60 lbs)		
Chiller	65 kg (144 lbs)		
Electrical Service			
Power Supply	Single-phase: 200-240 VAC, 50/60 Hz operating current: 10A, max current: 20A		
Chiller	Single-phase: 230 ±10% VAC, 20A, 50/60 Hz operating current: 12A, max current: 20A		
Temperature & Humi	dity		
Operating Temperature	15 to 35° C		
Storage Temperature	-20C to 50° C		
Relative Humidity	8-80%, non-condensing		
Control Interface			
Serial Interface	RS-232		
Rear Connections	External beam enable, external trigger		
Control Software	MS Windows-based Laser Commander		
Others			
Umbilical Length	3.65 m (12.0 ft); longer available upon request		


Air-water; water-water cooling option available

Cooling


# Terra PIV Physical Layout

AVOID EYE OR SKIN EXPOSURE TO DIRECT OR SCATTERED RADIATION


CE




#### Advantages Generation of Pulse Pairs



Generation of Pulse Pairs Flexible time delay adjustment



Two laser output synchronized to double the pulse energy and peak power, a) one laser output, b) a second laser output, and c) combined output.



Two laser output combined with an adjustable delay to double the repetition rate of the pulse. a) one laser output, b) a second laser output with delay, and c) combined laser output.



Diode pumped Nd:YLF laser



